
Support Units - Support Side, Round < Standard>

Standard




Part Number															B	BUR	BURM	BURR
Туре	No.	d	L	Н	F	D	Α	P.C.D.	В	V	d1	d2	l	Bearing Type	Retaining Ring	Unit Price	Unit Price	Unit Price
туре																1 ~ 10 pc(s).	1 ~ 10 pc(s).	1 ~ 10 pc(s).
BUR BURM BURR	6	6	10	6	4	22	36	28	28	17	3.4	6.5		B606ZZ	STWN, S6			
	10	8	12	7	5	28	43	35	35	22	3.4	6.5	6.5 4	B608ZZ	STWN, S8			
	12	10	15	7	8	34	52	42	42	26	4.5	8		B6000ZZ	STWN, S10			
	15	15	17	9	8	40	63	50	52	32	5.5	9.5	5.5	B6002ZZ	STWN, S15			
	20	20	20	11	9	57	85	70	68	47	6.6	11	6.5	B6204ZZ	STWN, S20			
	25	25	24	14	10	63	98	80	79	52	9	14	8.5	B6205ZZ	STWN, S25			



Part Number

BUN15 (Support side, separate item)

- ⑤ For details of Bearings mounting interface accuracies of Support Units, see Details of Bearing Nut ▶ P.759
- DLow Temperature Black Chrome Plating products are filled with low dust generation grease for cleanrooms.
- Store Accessories with care since they are required when assembling.



<SET parts> ■Black Oxide

BRW10-SET

BRW12-SET

BRW15-SET

BRW20-SET

BRW25-SET

SET parts SET Part Number Fixed Side Part Number Support Side Part Number **BRW6L-SET** BRW6L BUR6 **BRW6-SET** RRW6 BUR6 **BRW8S-SET** BRW8S BUR6 **BRW8-SET** BRW8 BUR6 BRW10S BRW10S-SET BUR10

BRW10

BRW12

BRW15

BRW20

BRW25

BUR10

BUR12

BUR15

BUR20

BUR25

	<u> </u>						
SET Part	SET parts						
Number	Fixed Side Part Number	Support Side Part Number					
BRWN6L-SET	BRWN6L	BURM6					
BRWN6-SET	BRWN6	BURM6					
BRWN8S-SET	BRWN8S	BURM6					
BRWN8-SET	BRWN8	BURM6					
BRWN10S-SET	BRWN10S	BURM10					
BRWN10-SET	BRWN10	BURM10					
BRWN12-SET	BRWN12	BURM12					
BRWN15-SET	BRWN15	BURM15					
BRWN20-SET	BRWN20	BURM20					
BRWN25-SET	BRWN25	BURM25					

■Electroless Nickel Plating

Low Temperature Black Chrome Plating							
SET Part	SET parts						
Number	Fixed Side Part Number	Support Side Part Number					
BRWR6L-SET	BRWR6L	BURR6					
BRWR6-SET	BRWR6	BURR6					
BRWR8S-SET	BRWR8S	BURR6					
BRWR8-SET	BRWR8	BURR6					
BRWR10S-SET	BRWR10S	BURR10					
BRWR10-SET	BRWR10	BURR10					
BRWR12-SET	BRWR12	BURR12					
BRWR15-SET	BRWR15	BURR15					
BRWR20-SET	BRWR20	BURR20					
BRWR25-SET	BRWR25	BURR25					