

DD3S series Display Units

7-segment digital display Super bright LED display and short body for up to 8 digits

- Super bright LED for easy reading
- Units can be combined together and installed into a panel cut-out.
- Decimal, hexadecimal, extra decimal display units are available.
- Positive or negative input logic
- Easy wiring and maintenance
- Power voltage 12 through 24V DC.
- Mother boards are available for dynamic and static display modes; substantial saving of wiring.



DD3S

Display Units (Housing Color: Black)

Notation	Function	Input Logic	LED Color	Part No.
Decimal	Standard	Positive	Red	DD3S-F31P-R
			Green	DD3S-F31P-G
		Negative	Red	DD3S-F31N-R
			Green	DD3S-F31N-G
	Zero-suppress	Positive	Red	DD3S-F31P-R-S
			Green	DD3S-F31P-G-S
		Negative	Red	DD3S-F31N-R-S
			Green	DD3S-F31N-G-S
Extra Decimal	Standard	Positive	Red	DD3S-F34P-R
			Green	DD3S-F34P-G
		Negative	Red	DD3S-F34N-R
			Green	DD3S-F34N-G
	Zero-suppress	Positive	Red	DD3S-F34P-R-S
			Green	DD3S-F34P-G-S
		Negative	Red	DD3S-F34N-R-S
			Green	DD3S-F34N-G-S
Hexadecimal	Standard	Positive	Red	DD3S-F36P-R
			Green	DD3S-F36P-G
		Negative	Red	DD3S-F36N-R
			Green	DD3S-F36N-G
	Zero-suppress	Positive	Red	DD3S-F36P-R-S
			Green	DD3S-F36P-G-S
		Negative	Red	DD3S-F36N-R-S
			Green	DD3S-F36N-G-S

Ordering Information

1. Specify the Part No. and quantity of the display units and accessories.

(Example) Display Unit	DD3S-F31P-R	8 pcs
Accessories		
• Spacer Unit	DD9Z-FY1-B	1 pc
• End Plate	DD9Z-W-B	1 set
• Mother Board	DD9Z-MB1-4	2 pcs

2. Order spacer units, end plates, and mother boards separately.
See the next page.